

Product manual



MoYE[®]
Endless
Possibilities

Aurras 2 True Wireless Earphone

Product diagram



Paired connection

1. Open the charging compartment cover, the headset will automatically power on and pair.



1. Power on pairing



2. Waiting for connection

Headphone function definition

1. Power On: the headset is automatically turned on and paired when the cover is opened in the charging compartment
2. Shut down: enter the charging compartment and close the lid to shut down
3. Automatic pairing mode: enter the automatic pairing mode after the boot is successful
4. The main and auxiliary units are successfully paired: the main and auxiliary units have no indicators lights
5. The mobile phone is successfully connected: the main and auxiliary phones have no indicator lights
6. Bluetooth disconnection: The phone actively disconnects Bluetooth.
7. Change the Bluetooth name: Find the name of the currently connected headset in the Bluetooth settings, click the icon on the right, click the name, you can edit the name, click finish.
8. Play and pause music: one touch.
9. Previous song/Next song: Double click on the left earphone is the previous song, and double click on the right earphone is the next song.
10. Increase/decrease volume: Click three times on the right to increase the volume, and click three times on the left to decrease the volume.
11. Call Siri: Long press for two seconds
12. Answer incoming call: touch any earphone under incoming call
13. Call status: during a Bluetooth call, the main and auxiliary phones are off.
14. Hang up the call: touch any headset while in a call
15. Reject: press and hold the headset for two seconds in the incoming call state
16. Low battery warning notes: report low battery warning when the battery voltage is lower than 3.4V (report once every 60 seconds)
17. Shutdown voltage: the battery voltage is lower than 3.2V to shut down immediately
18. Charging: the headset does not light up
19. Charging is complete: "4.2 full charge, automatic shutdown after full charge"
20. Sleep state: no connection after pairing, shut down in 3 minutes.
21. iPhone battery level display: Bluetooth connection is successful, and the iPhone has no battery icon displayed. (Playing status)
22. iPhone volume synchronization: Bluetooth connection is successful, the volume of the machine is synchronized with the volume of the phone (playing state).
23. Auto reconnect: after the headset is turned on again, the Bluetooth will automatically reconnect to the phone.

24. Automatically connect back when disconnected from a long distance: Disconnect from a long distance and return to Bluetooth to automatically connect to the hand within 8 meters
25. Automatically shut down when charging: Playback, sleep, stand by, and the headset will shut down when it enters the warehouse
26. Positioning function: After the headset is connected to the mobile phone, find the search APP in the mobile phone and open it, and select the name of the currently connected headset in my device. At this time, the headset is displayed on the map. Click to play the sound, and the headset will give an alarm. Sound.
27. Charging mode: when charging with the data cable plugged into the cradle, the orange indicator light flashes slowly, and the orange light is on when it is full
28. Smart sleep mode: When you don't need to use it and are no longer connected to the device, it will automatically shut down in about 5 minutes.
29. Charging mode: the earphones charge after the cover of the charging compartment is closed.

Product parameter

Bluetooth chip: Jerry Bluetooth version: V5.1 Pairing name: Pro6
Bluetooth Profile: HSP, HFP, A2DP, AVRCP, SPP, CVC
RF carrier frequency: 2402MHz-2480MHz
Bluetooth receiving distance: straight line barrier-free-10 meters
Input voltage: DC5V (The output current of the charger must be greater than 500mA). This headset is embedded with the rechargeable polymer lithium battery. Please fully charge the battery before using it for the first time.

Serious warning

Do not use this product while charging, please use the adapter specified by the manufacturer to charge the product. Do not disassemble the built-in lithium electronic battery and place it in the fire, do not allow metal products to touch or short circuit the electrodes, do not hit or squeeze the battery, and avoid placing it in the humid, corrosive or overheated (>60°C) environment.

Korisničko Uputstvo



MoYE[®]
Endless
Possibilities

Aurras 2 Bežične Slušalice

Dijagram proizvoda



Uparivanje

1. Otvorite poklopac odeljka za punjenje, slušalice će se automatski uključiti i upariti.



1. Uključite uparivanje



2. Čeka se povezivanje

Opis funkcije slušalice

1. Uključivanje: slušalice se automatski uključuju i uparuju kada se otvori poklopac odeljka za punjenje.
2. Isključivanje: udite u odeljak za punjenje i zatvorite poklopac kako biste ga isključili.
3. Režim automatskog uparivanja: udite u režim automatskog uparivanja nakon uspešnog pokretanja.
4. Glavna i pomoćna jedinica su uspešno uparene: glavna i pomoćna jedinica nemaju indikatorske lampice
5. Mobilni telefon je uspešno povezan: glavni i pomoćni telefoni nemaju indikatorske lampice
6. Prekidanje Bluetooth veze: telefon aktivno prekida Bluetooth vezu.
7. Promenite Bluetooth ime: pronađite naziv trenutno povezanih slušalica u Bluetooth podešavanjima, kliknite na ikonu sa desne strane, kliknite na ime, i možete da izmenite ime, kliknite na finish.
8. Pustite i pauzirajte muziku: jednim dodirom.
9. Prethodna pesma/Naredna pesma: Dvostruki klik na levu slušalicu je prethodna pesma, a dvostruki klik na desnu slušalicu je sledeća pesma.
10. Povećanje/smanjivanje jačine zvuka: Kliknite tri puta na desnoj strani kako biste povećali jačinu zvuka i kliknite tri puta na levoj strani kako biste smanjili jačinu zvuka.
11. Pozovite Siri: Pritisnite i zadržite dve sekunde
12. Odgovorite na dolazni poziv: dodirnite bilo koju slušalicu ispod dolaznog poziva
13. Status poziva: tokom Bluetooth poziva, glavni i pomoćni telefoni su isključeni.
14. Prekidanje poziv: dodirnite bilo koju slušalicu tokom poziva
15. Odbijanje: pritisnite i držite slušalice dve sekunde u stanju dolaznog poziva
16. Ton upozorenja o niskom nivou baterije: upozorenje o niskoj bateriji kada je napon baterije niži od 3.4 V (jednom svakih 60 sekundi)
17. Napon isključivanja: napon baterije je niži od 3.2 V da bi se odmah isključilo
18. Punjenje: slušalice ne svetle
19. Punjenje je završeno: 4,2 punjenje punjenja, automatsko isključivanje nakon punog punjenja"
20. Stanje spavanja: nema veze nakon uparivanja, isključuje se za 3 minuta.
21. Prkaz nivoa baterije iPhone-a: Bluetooth veza je uspešna, a iPhone nema prikazanu ikonu baterije. (Status igranja)
22. iPhone sinhronizacija jačine zvuka: Bluetooth veza je uspešna, jačina zvuka je sinhronizovana sa jačinom zvuka telefona (stanje reprodukcije).
23. Automatsko ponovno povezivanje: Nakon što se slušalice ponovo uključe, Bluetooth će se automatski ponovo povezati sa telefonom.

24. Automatski se ponovo povežite kada se prekinete sa velike udaljenosti: Prekinite vezu sa velike udaljenosti i vratite se na Bluetooth da biste se automatski povezali sa rukom u krugu od 8 metara.
25. Automatski se isključuje prilikom punjenja: reprodukcija, spavanje, pripravnost, slušalice će se isključiti kada uđu u skladište.
26. Funkcija pozicioniranja: Nakon što su slušalice povezane sa mobilnim telefonom, pronađite aplikaciju za pretragu u mobilnom telefonu i otvorite je, i izaberite naziv trenutno povezanih slušalica na mom uređaju. U ovom trenutku, slušalice su prikazane na mapi. Kliknite za reprodukciju zvuka i slušalice će reprodukovati zvuk alarma.
27. Punjenje kutije za punjenje: Prilikom punjenja sa kablom za prenos podataka priključenim na postojeće, narandžasta indikatorska lampica polako treperi, a narandžasta lampica svetli kada je puna
28. Pametni režim mirovanja: Kada ne morate da ga koristite i više niste povezani sa uređajem, automatski će se isključiti za oko 5 minuta.
29. Način punjenja: slušalice se pune nakon što se poklopac odeljka za punjenje zatvori.

Parametri proizvoda

Bluetooth čip: Jerry Bluetooth verzija: V5.1 Naziv uparivanja: Pro6
Bluetooth profil: HSP, HFP, A2DP, AVRCP, SPP, CVC
Frekvencija RF nosača: 2402MHz-2480MHz
Udaljenost bluetooth prenosa: pravolinijski bez prepreka >10 metara
Ulazni napon: DC5V (Izlazna struja punjača mora biti veća od 500mA). U slušalice je ugrađena polimer litijumska baterija koja se može puniti. Napunite bateriju pre prve upotrebe

Upozorenje

Nemojte koristiti ovaj proizvod tokom punjenja, za punjenje proizvoda koristite adapter koji je naveo proizvođač. Nemojte rastavljati ugrađenu litijumsku elektronsku bateriju i stavljati je u vatru, ne dozvolite da metalni proizvodi dodiruju ili kratko spoje elektrode, nemojte udariti ili stiskati bateriju i izbegavajte da je stavljate u vlažnu, korozivnu ili pregrejanu (>60°C) okolinu.